

Speakers Timer



turn button to set the desired time (minutes)

press button to start timer

dots are flashing timer is running...



press button to pause timer

press button to resume timer

time is over when last LED turns on. BAR starts to flash after 5% overtime (default setting)



press button to reset flashing bar

to reset timer any time, keep button pressed 3s. Press again to reset flashing bar.

Messaging



press button when display shows "gC"

turn button to select desired message (1-9)

press button to initiate message

Note:

Messaging can be used any time while timer is running, and will not affect time.

By default, **only the short display** shows the message. This prevents from showing messages to the audience when using multiple displays.



press button when display shows "gC" to return to timer setting mode

Message examples:

Messages are moving light patterns, which can be broadcast to the speaker. Before a speech, a meaning of those patterns can be negotiated.


- 1: speak faster
- 2: speak slower
- 3: come to the point
- 4: be more divergent
- 5: Audience has questions

- 6: change the subject
- 7: bad topic!
- 8: talk more about this
- 9: bravo!!!

Messaging display select:



when in messaging mode, turn button to 'd' and press.



turn button to dial the desired display type and press.



short display only (default)



long display only



short and long display



local controller display only

Dial 'gC' and press button to return to messaging mode.

Extended Time



press button when display shows "et"


display shows "%", which is the default setting (5% ext. time)

dial desired extra time and press button


Note:

Extended time setup can be used any time while timer is running, and will not affect time.

After extended time was set, both dots flash at the same time during timer run, instead alternating. This indicates that extended time is active.



dial "gC" and press button to return to timer setting mode



after regular time is over - extended time will show by turning LEDs off. Bar starts to flash.

extended time is over when last LED turns off. Bar starts to flash.